



© Euro Radio Co

© Euro Radio Co

© Euro Radio Co

© Euro Radio Co

NOTE:
 Diodes 1S2075 can be replaced with 1N4148.
 Stuck in TX,
 Check C117, change it to a 16 volt type.
 No RX/TX,
 Check for 5 volts at PLL (C112, R86 and R94).
 No RX and no channel display,
 Check R103 for cold solder joint.
 No TX audio and PA not working,
 Check TR17 is turn on, you may
 find it is missing Base volts (R70).
 AWI LED always on,
 Check TR24 known to go short.

CH1 = 10.270 MHz
 CH2 = 10.730 MHz

NOTE:
 Components with (?) marks, values, and or circuit reference
 note known. If anyone knows, The correct values and or circuit
 reference please E-Mail me and I will correct them.