

CIRCUIT SYMBOL	DESCRIPTION	PE'S PART NO.	CIRCUIT SYMBOL	DESCRIPTION	PE'S PART NO.
CAPACITORS (Continued)			CAPACITORS (Continued)		
C-17,80,83,131,200,210,240	Mylar Condenser	0.01 μ F 50V K 1800-407	C-403,405,406,407,408	Ceramic Condenser	0.01 μ F 50V Z ZF. 1800-112
C-23,51,72,74,86	Mylar Condenser	0.022 μ F 50V K 1800-408	C-19,20,21,22,28,33,34,41,57,100,105,106,109,118,146,156,193,196,202,206,215,216,217,219,220,223,227,228,248,708,709,713	Ceramic Condenser	0.022 μ F 50V Z ZF. 1800-079
C-703,704	Mylar Condenser	0.033 μ F 50V K 1800-418			
C-18,25,26,27,29,30,31,40,64,85,121,157,194,198,260	Mylar Condenser	0.039 μ F 50V K 1800-409			
C-61,62,82,169,401,245	Mylar Condenser	0.047 μ F 50V K 1800-411			
C-71	Mylar Condenser	0.068 μ F 50V K 1800-410			
C-73,75,91,96,133,134,175,188,191,231,153	Mylar Condenser	0.1 μ F 50V K 1800-412			
C-168	Ceramic Condenser	0.5pF 50V C CH. 1800-002	CT-1,2,3,4,5,6,7	Trimmer Condenser	CV-020 20P 1800-203
C-117,155	Ceramic Condenser	1pF 50V C CH. 1800-003	RR-401,402	Compound Parts	HA-008 680 ohm x 7 1900-402
C-37	Ceramic Condenser	2pF 50V C CH. 1800-004	RR-701	Compound Parts	HA-016 1900-404
C-32,288	Ceramic Condenser	5pF 50V D CH. 1800-095	CC-1,2	Compound Parts	HA-003 1800-103
C-143	Ceramic Condenser	7pF 50V D CH. 1800-058			
C-271,36	Ceramic Condenser	3pF 50V C CH. 1800-094			
C-116,130,139,150,154	Ceramic Condenser	10pF 50V J CH. 1800-059			
C-111,112	Ceramic Condenser	18pF 50V J CH. 1800-060			
C-54	Ceramic Condenser	22pF 50V J CH. 1800-061	X-1	Crystal	QX-017 2100-004
C-236,244	Ceramic Condenser	33pF 50V J CH. 1800-062	X-2	Crystal	QX-054 2100-005
C-1,163,274	Ceramic Condenser	39pF 50V J CH. 1800-063	X-5	Crystal	QX-080 2100-009
C-7,45,122,123,242	Ceramic Condenser	47pF 50V J CH. 1800-064	X-4	Crystal	QX-081-001 2100-006
C-24,174,176	Ceramic Condenser	56pF 50V J CH. 1800-065	X-6	Crystal	QX-081-002 2100-007
C-257,93,142,164	Ceramic Condenser	68pF 50V J CH. 1800-066	X-3	Crystal	QX-081-003 2100-008
C-115,268	Ceramic Condenser	100pF 50V K CH. 1800-067			
C-184	Ceramic Condenser	82pF 50V J CH. 1800-097			
C-165	Ceramic Condenser	180pF 50V K CH. 1800-069	FT-1	Crystal Filter	FL-001 2100-001
C-173	Ceramic Condenser	220pF 50V K RH. 1800-098	FT-2	Crystal Filter	FL-046 2100-002
C-258	Ceramic Condenser	330pF 50V K SL. 1800-040	S-405	Rotary Switch (CH)	SR-190 3000-108
C-38	Ceramic Condenser	330pF 50V K UJ. 1800-071	S-403	Rotary Switch (Meter)	SR-187 3000-109
C-167	Ceramic Condenser	390pF 50V K UJ. 1800-072	S-402	Push Switch(Mode, PA, ANL)	SW-109 3000-006
C-170	Ceramic Condenser	470pF 50V K UJ. 1800-073	S-404	Push Switch (scan)	SW-118 3000-007
C-8	Ceramic Condenser	100pF 50V K SL. 1800-052	SP-401	Speaker	SP-049 3100-006
C-269	Ceramic Condenser	250pF 50V K SL. 1800-109	M-401, PL-401	Meter	MT-143 2900-008
C-128,137,148	Ceramic Condenser	220pF 50V K SL. 1800-054	Relay-1	Relay	RL-027 2400-002
C-125	Ceramic Condenser	270pF 50V K SL. 1800-075	MIC	Microphone	MK-070 3200-003
C-127,136,147,270	Ceramic Condenser	470pF 50V K SL. 1800-074	J-401	Antenna Connector	JK-068 1100-018
C-9,113,114,265,711,712,415,416	Ceramic Condenser	0.001 μ F 50V K YB. 1800-110	J-402	Metal Consent	JK-072 1100-007
C-10,11,12,13,243,285,286,159,160,161,162,166,172,177,178,183,185,186,187,189,225,272,222,239	Ceramic Condenser	0.0047 μ F 50V K YB. 1800-024	J-406	3F Consent	JK-052 1100-003
C-266,277,278,260,265,282	Ceramic Condenser	0.047 μ F 50V Z ZF 1800-111	J-403,404	Jack	JK-010 1100-001
C-2,4,6,5,15,16,46,53,124,129,138,149,151,152,190,192,195,204,205,207,208,209,214,247,249,705,262,261,246	Ceramic Condenser	0.01 μ F 50V K YB 1800-025	J-410	L.E.D. Connector	JK-073-002 400m/m 1100-012
C-250,251	Ceramic Condenser	0.01 μ F 25V Z ZF 1800-108	J-411	L.E.D. Connector	JK-073-003 250m/m 1100-019
			J-412	L.E.D. Connector	JK-073-005 1100-020
				FPC	JK-074 1100-017
				Relay Socket 1400-001
				Crystal Socket	TP-019 1100-801
			TP-6,7,8,9	Check Terminal	TP-027 1100-802
			TP-2,4	Check Terminal	FS-001 2800-005
				Fuse	YD-003-003 3400-233
				Mica Insulation Board	YD-038 3400-234
				Mica Insulation Board	YD-035 3400-228
				Heat Sink	YY-027 3400-225
				Alumina Insulation Board	YY-036 1100-504
				Tight Bush	

CIRCUIT
SYMBOL

DESCRIPTION

PE'S
PART NO.

MISCELLANEOUS (Continued)

Relay Hook Pin	YY-046	1200-005
Wire Clamper	YY-047	1100-804
DC Cord	W-070088	2700-001
Flat Cable	WF-105	2700-104
Connector Cord	WZ-031	2700-003
Chassis		3300-821
Case (top)		3300-112
Case (bottom)		3300-113
Front Chassis		3300-822
Baffle panel		3400-229
P.C.B. Holder (large)		3300-823
P.C.B. Holder (small)		3300-824
Switch Angle		3300-825
Bracket		3300-208
Meter Holder		3300-801
Shield Panel		3400-203
Shield Panel		3400-223
Mike Hunger		3300-401
Spring Nut		1100-761
Earth Lug		1100-806
Front Panel (silver)		3400-230
Channel Knob		1300-004
Knob (lugged)		1300-002
Knob (out)		1300-011
Knob (in)		1300-012
Knob (Minus shape)		1300-005
Push Knob		1300-010
Push Knob (black)		1300-016
Push Knob (orange)		1300-017
L.E.D. Cap		3400-002
L.E.D. Holder (front)		3400-008
L.E.D. Holder (back)		3400-009
Control Plate		3400-513
F.C.C. Plate		1700-010
Warning Label		1700-402
Control No. Seal		1700-201
Warranty Tag		1600-002
Bracket Angle		3300-826
Screw for Mounting Bracket		1100-718
Speaker Net		3400-231
Rubber Washer for Speaker		1100-319
Rubber Washer for Bracket		1100-315
Fiber Washer for Bracket		1100-303
Meter Cushion		1100-407
Insulation Board (small)		3400-207
Insulation Board (large)		3400-232
Panel Protection Cover		3300-114
Chassis Protection Cover		3300-115
Tapping Screw	M3 x 6	1100-702
Tapping Screw	M3 x 8	1100-719
Bind Screw	M2.6 x 10	1100-721
Bind Screw	M2.6 x 12	1100-762
Bind Screw	M3 x 6	1100-704
Bind Screw	M3 x 8	1100-752
Bind Screw	M2.6 x 6	1100-755

CIRCUIT
SYMBOL

DESCRIPTION

MISCELLANEOUS (Continued)

Round Tapping Screw	5φ x 10	1100-709
Round Tapping Screw	3.5φ x 8	1100-708
Round Tapping Screw	M3 x 6	1100-725
Round Tapping Screw	M3 x 8	1100-763
Hexagon Nut	M2.6	1100-737
Frage Nut	M3	1100-764
Spring Washer	2.6φ	1100-759
Lugged Washer	3.5	1100-742
Lugged Washer	5	1100-743
Knob Spring	3.5φ No. 7800.	1100-309
Knob Spring	6φ No. 8500.	1100-310
Knob Spring	6φ No. 6600.	1100-305
Rivet	3.2φ x 5	1100-308
Banc-loc	M3	1100-326
Lug Terminal	3φ	1100-307
Styrofoam (front)		1800-006
Styrofoam (back)		1800-007
Display Box		1800-212
Double Carton		1800-307
Instruction Manual		1600-110
Wiring Diagram		1600-610
Warranty Card		1600-201
F.C.C. Application Form		1600-301
F.C.C. Temporary License Form		1600-401
Instruction book for F.C.C. Rules Part 95		1600-501
Printed Circuit Board	PC-346AA	3500-014
Printed Circuit Board	PC-243AA	3500-016
Printed Circuit Board	PC-275AB	3500-017
Printed Circuit Board	PC-291AA	3500-018
Printed Circuit Board	PC-292AA	3500-019
Printed Circuit Board	PC-293AA	3500-020
Flexible P.C.B.	PC-255AA	3500-021

PE'S
PART NO.